



PX100, PX300 & PX600 Series Safety Transformers



These Safety Transformers are specifically designed to supply 12 volts to pool/spa lights, submersible fixtures and outdoor garden lights. A grounded shield between the primary and secondary windings assures safe operation and the built-in circuit protection will disconnect power to the transformer in case of defect or overload.

Applications

- Pool Lights
- Spa Lights
- Garden Lights
- Fountain Lights

Specifications - PX100/S, PX300/S

Enclosure – 7.25" (19.4 cm) H x 5.25" (13.3 cm) W x 4.5" (11.4 cm) D. Stainless steel or steel with electrostatically applied light beige finish. Mounting brackets top and bottom.

Knockouts – Total of ten combination 1/2"-3/4" knockouts, (2) right side, (2) left side, (2) back, (4) bottom.

Electrical Rating – See table.

Shipping Weight – See table.

Specifications – PX600/S

Enclosure – 10" (25.4 cm) high x 10" (25.4 cm) wide x 5" (12.7 cm) deep. Stainless steel or steel with electrostatically applied light beige finish. Mounting brackets top and bottom.

Knockouts – Two combination 1/2"-3/4", and 4 combination 3/4"-1" knockouts on the bottom. Total of six combination 1/2"-3/4" knockouts, (2) right side, (2) left side, (2) back.

Electrical Rating – See table.

Shipping Weight – See table.

Model #	Description	Input	Output	Shipping Weight
PX100	100 Watt Beige Steel Enclosure	120V, 1AMP	12 or 13V	7.0 lbs (3.2 kg)
PX100S	100 Watt Stainless Steel Enclosure	120V, 1AMP	12 or 13V	7.0 lbs (3.2 kg)
PX300	300 Watt Beige Steel Enclosure	120V, 3AMP	12,13 or 14V	13.0 lbs (5.9 kg)
PX300S	300 Watt Stainless Steel Enclosure	120V, 3AMP	12,13 or 14V	13.0 lbs (5.9 kg)
PX600	600 Watt Beige Steel Enclosure	120V, 6AMP	12,13 or 14V	26.0 lbs (11.7 kg)
PX600S	600 Watt Stainless Steel Enclosure	120V, 6AMP	12,13 or 14V	26.0 lbs (11.7 kg)



PX100



PX100S



PX300



PX300S



PX600



PX600S